

## ESE 15 YW-B

14,3/13,0kVA ENDRESS Construction site - generator

SKU: E310011



### TECHNICAL ATTRIBUTES

|                                    |                                                                                                |                                        |             |
|------------------------------------|------------------------------------------------------------------------------------------------|----------------------------------------|-------------|
| <b>Modell</b>                      | Yanmar 3TNV88-BGPGE                                                                            | <b>No. of motor cylinders and type</b> | 3L          |
| <b>Measurements L x W x H mm</b>   | 1646 x 885 x 1061                                                                              | <b>Nominal voltage V</b>               | 400/230     |
| <b>Weight (kg) ~</b>               | 480                                                                                            | <b>Nimellisvirta 3~ (PRP) A</b>        | 0,755555556 |
| <b>Alternator type</b>             | synchron                                                                                       | <b>Fuel</b>                            | Diesel      |
| <b>Sockets</b>                     | CEE 400V / 32A 1x<br>CEE 400V / 16A 1x<br>CEE 230V / 16A 2x<br>230V / 16A<br>Sukopistorasia 1x | <b>Main circuit breaker [Pole]</b>     | 3           |
| <b>Displacement [cm3]</b>          | 1642                                                                                           | <b>Max. Output [LTP] [kVA/kw]</b>      | 14,3/11,44  |
| <b>Jatkuva teho (PRP) kVA/kW</b>   | 13.0/10.4                                                                                      | <b>Fuel tank capacity [l]</b>          | 51          |
| <b>Fuel cons. at 75% PRP [L/h]</b> | 2                                                                                              | <b>Frequency Hz</b>                    | 50          |
| <b>Start-up system</b>             | Sähkökäynnistin                                                                                | <b>Power factor (Cos theta)</b>        | 0,005555556 |
|                                    |                                                                                                | <b>Sound pressure level LPA db(A)</b>  | 93          |