

## ESE 455 VW/AS

415,8kVA ENDRESS POWER Line -generator with electric start

SKU: E331271



Abbildung ähnlich /  
Illustration similar

### TECHNICAL ATTRIBUTES

|   |                        |   |                         |
|---|------------------------|---|-------------------------|
| <b>Modell</b>                                 | 6-cylinder 4-stroke    | <b>Max. Output [LTP] kVA / kW 3 ~</b>       | 456,8 / 365,4<br>kVA/kW |
| <b>Measurements L x W x H mm</b>              | 3951 x 1438 x 2085     | <b>Engine output (LTP) kW</b>               | 369,0kW                 |
| <b>Weight (kg) ~</b>                          | 3671kg                 | <b>Nominal voltage V</b>                    | 400V 3~ /230V<br>1~     |
| <b>Running time at 75% load (h)</b>           | 9,3h                   | <b>Nominal current / Cos theta</b>          | 600,2A 3~ /0,8          |
| <b>Insulation</b>                             | Luokka H               | <b>Continuous power [PRP] kVA / kW 3 ~</b>  | 415,8 / 332,6<br>kVA/kW |
| <b>Kühlanlage</b>                             | water cooled           | <b>Fuel tank capacity [l]</b>               | Diesel / 636            |
| <b>Revolutions per minute (rpm) / control</b> | 1500/ Electronic       | <b>Alternator model</b>                     |                         |
| <b>Fuel cons. at 75% PRP [L/h]</b>            | 68,2l                  | <b>Sound pressure level LPA (7m) db (A)</b> | 72 db(A)                |
| <b>Volume</b>                                 | 12 780 cm <sup>3</sup> | <b>Sound pressure level LPA db(A)</b>       | 97 db(A)                |
| <b>Start-up system / battery</b>              | Electric starter 24V   | <b>Frequency / regulation</b>               | 50 Hz / electric        |