

## ESE 606 DHG-GT DUPLEX

6,6 / 6,0kVA ENDRESS DUPLEX Plus Line generator

SKU: E113556



### TECHNICAL ATTRIBUTES

<b>Model</b>	Honda GX 390	<b>Nominal current A</b>	8,7 A
<b>Measurements L x W x H mm</b>	780 x 550 x 595 mm	<b>Fuel</b>	Bensiini
<b>Weight (kg) ~</b>	104kg	<b>Garden tools up to</b>	3200 W
<b>Running time at 75% load (h)</b>	15,5h	<b>Protection class</b>	54 IP
<b>Shockproof sockets</b>	2 x 230 V/16 A 1 x CEE 400 V/16 A	<b>Fuel tank capacity [l]</b>	33l
<b>Continuous power</b>	6,0 / 4,8 kVA/kW	<b>Frequency Hz</b>	50 Hz
<b>Kompressorit ja pumput enint.</b>	2400 W	<b>Power 3000 r/min speed kW</b>	6,4 kW
<b>Fuel cons. at 75% PRP [L/h]</b>	2,1l	<b>Power factor (Cos theta)</b>	0,8 cos φ
<b>Volume</b>	389 cm <sup>3</sup>	<b>Alternator model</b>	Duplex
<b>Start-up system</b>	Narukäynnistin	<b>Sound pressure level LPA (7m) db (A)</b>	60 db(A)
<b>Possible applications</b>	400 V	<b>Sound pressure level LPA db(A)</b>	97 db(A)
<b>Max. Output [LTP] kVA/kW</b>	6,6 / 5,3 kVA/kW	<b>Electric tools up to</b>	4700 W
<b>No. of motor cylinders and type</b>	Yksisylinterinen nelitahtinen	<b>Electric devices up to</b>	4800 W
		<b>Welding tools up to</b>	3,25 mm ø

**Nominal voltage V**

400 V