

## ESE 908 DBG ES DUPLEX SILENT

9,9 / 9,0kVA ENDRESS DUPLEX Silent Line generator with electric start

SKU: E113007



### TECHNICAL ATTRIBUTES

<b>Model</b>	B&S Vanguard 16 HP	<b>Possible applications</b>	400V
<b>Measurements L x W x H mm</b>	820 x 440 x 580	<b>No. of motor cylinders and type</b>	2-Sylinteri 4-Tahti OHV
<b>Weight (kg) ~</b>	132	<b>Nominal voltage V</b>	400/230
<b>Elektroniset kuluttajat enint</b>	6400W	<b>Nominal current A</b>	12.9/26.1
<b>Alternator type</b>	DUPLEX	<b>Fuel</b>	Bensiini
<b>Invertterihitsauskoneet enint</b>	4,0mm	<b>Puutarha- tai rakennuskoneet enint</b>	4300W
<b>Sockets</b>	3 x 230 V/16 A1 x CEE 230 V/16 A1 x CEE 400 V/16 A	<b>Engine build</b>	0.8
<b>Displacement [cm3]</b>	479	<b>Max. output 1~ [kVA/kW]</b>	6.0/5.4
<b>Jatkuva teho 1~ kVA/kW</b>	5.5/5.0	<b>Max. output 3~ [kVA/kW]</b>	9.9/7.9
<b>Jatkuva teho 3~ kVA/kW</b>	5.5/5.0	<b>Power tools up to</b>	6300W
<b>Kompressorit ja pumput enint.</b>	3200W	<b>Fuel tank capacity [l]</b>	12
<b>Kotelointiluokka generaattori IP</b>	54	<b>Frequency Hz</b>	50
<b>Fuel cons. at 75% PRP [L/h]</b>	2.4	<b>Power 3000 r/min speed kW</b>	9.5
<b>Start-up system</b>	Sähkökäynnistin	<b>Power factor (Cos theta)</b>	0.8
		<b>Sound pressure level LPA db(A)</b>	89

