

Outlets: 1 x CEE 63 A, 1 x CEE 32 A, 1 x CEE 16 A, 1 x CEE 230 V/16 A, 1 x Schuko 230 V/16 A.

Endress ESE 100 IW/RS is a 1500 rpm synchronous generator with a continuous output of 94 kVA / 75.2 kW. It has AVR voltage regulation, a Stage V engine and an extended fuel tank.

TEKNISET TIEDOT

Tuotekoodi	E335277
Continuous power (PRP)	94 / 75,2 kVA/kW
Engine continuous power (PRP)	85,5 kW
Nominal voltage	400/230 V
Nominal current 3~ (PRP)	135,8 A
Frequency	50 Hz
Sockets	1 x CEE 400 V/63 A, 1 x CEE 400 V/32 A, 1 x CEE 400 V/16 A, 1 x CEE 230 V/16 A, 1 x Schuko 230 V/16 A
Engine	FPT F36ETVP03.A94, Stage V

Displacement	3600 cm³
Rotational speed	1500 r/min
Fuel	Diesel
Fuel cons. at 75% PRP	15,5 l/h
Running time at 75% load	27,1 h
Sound power level LWA	97 dB(A)
Sound pressure level LPA (7m)	72 dB(A)