

Spine Plug & Play 16A connects the site’s electrical board to the Spine cloud service without any separate installation work. The enclosure comes with the current transformers and antenna pre-wired, and setup is done with the QR code on the enclosure.

PÄÄOMINAISUUDET

- Rated current 16A, rated voltage 400 V
- Connects between the board and the supply cable with an extension socket and plug
- 50 cm 5×2.5 H07RN-F cables at both ends
- Weight 1.8 kg, dimensions 25.5 x 18 x 11 cm
- Setup with a QR code, no separate programming

TEKNISET TIEDOT

Tuotekoodi	501310005	**Cable length**	2 x 50 cm
Nominal Current	16 A	**Measurements**	25,5 x 18 x 11 cm
Nominal voltage	400 V	**Weight**	1,8 kg
Cable	5×2,5 H07RN-F		